

CDJBS12 TO CDT2S12VIFW ASSEMBLY

1. Remove Camera and junction box from packaging.



2. Loosen the three (3) security bolts that fasten the Dome to the camera using the supplied security wrench.



3. Use a Phillips screwdriver to remove the three (3) bolts that secure the Camera to the back housing.



4. Remove the camera from the back housing by twisting the back housing counterclockwise and pulling down.



5. Using a Phillips screwdriver remove the three (3) bolts that secure the multi-purpose mounting plate from the junction box.



6. Discard the multi-purpose mounting plate.



CDJBS12 TO CDT2S12VIFW ASSEMBLY

7. Remove the two (2) security bolts from the hardware bag.



8. Insert the two (2) security bolts into the junction box cover. Use the supplied security wrench to tighten the three security bolts.



9. Remove the three (3) short Phillips head bolts from the hardware bag.



10. Place the camera back housing onto the junction box. Notice the orientation below.



11. Use a Phillips screwdriver to secure the three (3) short bolts to mount the camera back housing to the junction box.



12. Remove the twist tie from the camera main cable. Make the video and power connections. Feed the excess cable into the junction box.



CDJBS12 TO CDT2S12VIFW ASSEMBLY

13. Reinsert the camera into the back housing. Turn clockwise to line up the three (3) bolt holes. Use a Phillips screwdriver to secure the three (3) bolts.



14. Use the supplied security wrench to tighten the three (3) security bolts on the camera dome.



15. The assembly is complete.

